

## LED Filament G125 Dimmable




Energy saving LED 125mm Globe replacement lamp featuring LED filament technology and antique bronzed coloured glass to closely resemble the look and feel of a traditional filament incandescent lamp.

- Exact equivalent brightness for regular 50W incandescent lamp
- 10,000 hour life
- 5,000 switching cycles
- 2200K extra warm white
- BC-B22d or ES-E27 cap
- Antique bronze finish
- Dimmable - compatible with both leading and trailing edge dimmers\*
- For indoor use only

Product Code	Watts (W)	Volts (V)	Cap	Colour Appearance	Colour Temp (K)	Initial Lumens (lm)	Incandescent Equivalent (W)	Dimensions (mm)		Energy Rating	Order Qty
								Dia	H		
<b>Single Carton</b>											
4306	7.5	240	BC-B22d	Extra Warm White	2200	638	50	125	175	A+	1
4313	7.5	240	ES-E14	Extra Warm White	2200	638	50	125	175	A+	1

\* The lamp is compatible with most dimmer switches, please refer to website for up-to-date list of compatible dimmer switches.



*We have valued our reputation since 1878, why risk yours with anyone else?*



# 7.5W LED Filament Dimmable ES-E27



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Tested Products: 4214, 4252, 4313



Manufacturer	Model	Compatible	Style of Dimmer	Dimming Level Minimum	Dimming Level Maximum	Number of Lamps Tested per Circuit
Aurora	AU-DSP401	✓	Leading Edge	0%	100%	1-5
Aurora	AU-DSP651	✓	Leading Edge	0%	100%	1-5
Aurora	AU-DSP400X	✓	Leading Edge	5%	100%	1-5
Danlers	DP1D 400WIET	✓	Leading Edge	0%	100%	1-5
Danlers	DSS1D 400W	✓	Leading Edge	30%	100%	1-5
Danlers	DPDLED	✓	Leading Edge	0%	100%	1-5
Danlers	DSS1D 250W	✓	Leading Edge	0%	100%	1-5
Eaton	P9131	✓	Leading Edge	0%	100%	1-5
MK	K1521WHILV	✓	Leading Edge	20%	100%	1-5
MK	K1524WHILV	✓	Leading Edge	20%	100%	1-5
MK	K4511xxxLV	✓	Leading Edge	15%	100%	1-5
Varilight	V-Pro JQP401W	✓	Trailing Edge	15%	100%	1-5
Varilight	V-Pro JQP252W	✓	Trailing Edge	15%	100%	1-5
Zano	ZANOMO500	✓	Leading Edge	0%	100%	1-5

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.  
Danlers: DQDGD EU400W

*We have valued our reputation since 1878, why risk yours with anyone else?*





# 7.5W LED Filament Dimmable BC-B22d



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Tested Products: 4207, 4245, 4306

Crompton Lamps recommends the use of Varilight V-Pro trailing edge dimmers



Manufacturer	Model	Compatible	Style of Dimmer	Dimming Level Minimum	Dimming Level Maximum	Number of Lamps Tested per Circuit
Aurora	AU-DSP401	✓	Leading Edge	5%	100%	1-3
Aurora	AU-DSP651	✓	Leading Edge	5%	100%	1-3
Aurora	AU-DSP400X	✓	Leading Edge	5%	100%	1-3
Danlers	DP1D 400WIET	✓	Leading Edge	5%	100%	1-3
Danlers	DPDLED	✓	Leading Edge	0%	100%	1-3
Danlers	DSS1D 250W	✓	Leading Edge	0%	100%	1-3
Eaton	P9131	✓	Leading Edge	5%	100%	1-3
MK	K1521WHILV	✓	Leading Edge	50%	100%	1-3
MK	K1524WHILV	✓	Leading Edge	50%	100%	1-3
MK	K4511xxxLV	✓	Leading Edge	40%	100%	1-3
Varilight	V-Pro JQP401W	✓	Trailing Edge	30%	100%	1-3
Zano	ZANOMO500	✓	Leading Edge	5%	100%	1-3

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.  
Danlers: DQDGD EU400W, DSS1D 400W

*We have valued our reputation since 1878, why risk yours with anyone else?*

